








One light head with an adapter for PALADIO TRACK (48V-DALI). Light head can be taken off and is fully adjustable through a magnetic hinge system. Light heads are available as flood or spot versions

(beam angle with lenses for 26 and 34 degrees). Cable suspensions are adjustable.

Design: Ulrich Sattler | Michael Schmidt, Code2design





STRUCTURE					S	TRUC	TURE								
Туре	WØ/Hmm	WØ/H inches	LED Watt	weight kg ²⁾ / lbs ²⁾	Type No. Finish DIM. Power Nounti Supply Versio Cable			ing in							
	Ø 196 / 270 mm	Ø 7.7 / 10.6"	12,5 W	1.6 / 3.5	1805.	xx.	xx. x	x. xx							
Finish 1 track adapter	14 black matt				XXXX.	14	xx. x	x. xx					<u> </u>		
Dimmer	DALI- Dimmi	-2 ng only with dimmable PALADIO TRACK			xxxx.	XX.	06 x	x. xx							
Power Supply	CASA	MBI* *Each head individually	switch- and dimmable	2	XXXX.	XX.	08 x	x. xx							
Cable	without power supply ca	ble			XXXX.	XX.	xx. 0	00 xx							
Mounting Version	Z				xxxx.	xx.	xx. x	x. 0Z							
	With Adapter for PALADIO TRACK System				1805. Order N STRUCT	14 o.	0	00 OZ			uci	IT HE			
LIGHT HEAD	(48V-DALI)								Type No.		Fi- nish	LE Kelvin	:D		
Туре									01	xx.	XX.	xx	XX.	xx	Ī
Finish 2 Light head outside ring 12 white matt 62 (14) black matt polished					Standard				XX.	12 62	XX.	xx xx	xx.		1
			polistied						xx.	22	XX.	xx	XX.	xx	2
Finish 3 Light head top cover	60 silver anodised 61 gold anodised 62 black anodised				Standard				XX.	60 61 62	XX	XX.	xx		
LED CRI >92 SELV	Warn	warm-white 2700 K n-white 3000 K							XX. XX.	XX. XX	XX.	30	XX. XX.	xx xx	
Beam Angle	FLOC	ral-white 4000 K DD 12,5 W 1282¹ Lumen				St:	andar	d	XX.	XX	XX.	40 xx	99		
-	SPOT SPOT	26° 12,5 W 1550¹ Lumen	UGR<19			3(6	unual	u	XX. XX.	XX	XX. XX. XX.	XX	26 34	00	

CASAMBI

CASAMBI wall-switch WALL SWITCH CASAMBI wall-switch

white black

207. 00.00.00.11 207. 00.00.00.10

Order No. LIGHT HEAD FLOOD

00 00

Casambi wall-switch is a wireless user interface that can be configured via the Casambi app. The four target buttons can control a scene or an animation of the user's choice or simply one luminaire, one luminaire group or all lights together if so desired. Up to 4 groups may be separately programmed. It comes with a wall mounting plate. The switch can be attached to the plate as it is equipped with magnets.











IP 20











