
## **AVVENI**

lightlight® Track system

**Product- Information:** Spot with adapter for LightLight® system from Buschfeld. Light head can be taken off and is fully adjustable through a magnetic hinge system. Light heads are available as flood or spot versions (lenses with 26 and 34 degrees). Cable suspensions are adjustable.

Design: AVVENI: Ulrich Sattler, Michael Schmidt, Code2design | LightLight®: Hans Buschfeld





	`Tiltable	V Rotatable			$\overline{}$	<b>V</b>											
TRACK ADAPTER STRUCTURE																	
Type L/Smm			/Smm inches	LED W	att	weight kg <sup>2)</sup> / lbs <sup>2)</sup>	Type No.	Finish 1	DIM.	Power Supply	tina						
,,,		_						-		Cable	Version		ou	SC	hf	el	d
	262 / 28	1	03" / 1.1"	12,5		0,5 / 1.1	1153.	XX.	XX.	XX.	XX.						
Finish 1	42			<b>I</b>			xxxx.	12	XX.	XX.	XX.						,,,,,,,
Structure		te matt . 9003	14 black matt	aluminium polished			XXXX. XXXX.	14 22	XX. XX.	XX. XX.	1 1				0		
Dimmer	without dimmer Standard								00	XX.	XX.	li	ghtl	igh:	HB		
	САЅАМВІ							xx.	08	XX.	XX.	[	Design:	Hans	Buscl	hfeld	
Power Supply Cable	power supply ca	able transparent					xxxx.	XX.	XX.	00	XX.						
Mounting							XXXX.	XX.	XX.	XX.	00						
Version	Р	C															
Please order mounting version separately										00	00						
							Order No.	STRUC	CTURE				110	GHT HE	AN		
pend36 ceiling36 in36												ype Fini No. 2			ED		
LIGHT HEAD												110.		Kelvin	Beam angle		
Туре											(	)1 x	c. xx.	xx	XX.	XX	XX
Finish 2 Light head	12		<b>62</b> (14)	22				S	tanc	larc	ı >	x. <b>1</b> 2	2 xx.	xx	xx.	XX	XX
outside ring		te matt . 9003	black matt	aluminium polished		$\square {\circ} ( \hspace{0.1cm} )$	)					x. 6			XX.		XX
	Finish 2 must b	oe the same as fir	ish 1									x. 2	2 xx.	XX	XX.	XX	XX
Finish 3 Light head	60		61	62				S	tanc	larc	ı >	x. x			xx.	XX	xx
top cover	silve	er dised	gold anodised	black anodised			)					(X. X)			XX.		XX
		<b>.</b>	L'1. 0700 K									(X. X)		+	XX.		XX
LED CRI >92	LED	Extra warm-v Warm-white	hite 2700 K 3000 K									(X.   X)			XX.		xx
SELV		Neutral-white										(X. X)			XX.		xx
Beam Angle		FLOOD	12,5 W   1282	2¹ Lumen			\	S	tanc	larc	ı	x. x	xx.	xx	99	00	00
	UGR<19	SPOT 26°	12,5 W   1550				1					x. x			26	00	
		SPOT 34°	12,5 W   1550	<sup>1</sup> Lumen			١				>	(X. X	( XX	. XX	34	00	00



Input voltage for all external power supply units and canopies is 220-240 VAC 50-60 Hz

Quantity

Order No. Accessories (page 2)



00 00 00 00













# **AVVENI**

## **ACCESSORIES**

### **CASAMBI WALL SWITCH**



CASAMBI wall-switch CASAMBI wall-switch white black 207. 00. 00. 00. 11 207. 00.00.00.10

Casambi wall-switch is a wireless user interface that can be configured via the Casambi app. The four target buttons can control a scene or an animation of the user's choice or sim ply one luminaire, one luminaire group or all lights together if so desired. Up to 4 groups may be separately programmed. It comes with a wall mounting plate. The switch can be attached to the plate as it is equipped with magnets.

**Ceiling Fixation** 



Consisting of a cavity ceiling box with 80mm round metal cover.

Applicable to mounting version B.

200. 00.00.00.11